

INSTALLATION / WARRANTY INSTRUCTIONS

issue date: DEC 2013

PierLUX Plus ~ PIERLUX/5/4K,PIERLUX/5/3K,PIERLUX/6/4K,PIERLUX/6/3K,PIERLUX/8/4K,PIERLUX/8/3K

PLEASE READ THESE INSTALLATION INSTRUCTIONS CAREFULLY BEFORE INSTALLING OR MAINTAINING THIS EQUIPMENT. THE PRODUCT IS DESIGNED FOR INSTALLATION AND MAINTENANCE IN ACCORDANCE WITH RELEVANT AUSTRALIAN STANDARDS (AS/NZ3000), THESE INSTRUCTIONS AND LOCAL REGULATIONS (WHERE APPLICABLE), BY AN AUTHORISED AND LICENCED ELECTRICIAN.

THE INSTALLATION INSTRUCTIONS WERE CORRECT AT THE TIME OF PRINT. TO REFLECT CHANGES IN TECHNOLOGY AND AUSTRALIAN STANDARDS; PIERLITE AUSTRALIA RESERVES THE RIGHT TO AMEND THE INSTRUCTIONS WITHOUT NOTICE. UPDATED GUIDELINES CAN BE FOUND ON www.pierlite.com.

IMPORTANT - THE PRODUCT MUST BE MAINTAINED AND OPERATED IN ACCORDANCE WITH THE MANUFACTURER'S INSTRUCTIONS, FAILURE TO DO SO MAY DAMAGE THE PRODUCT AND SERVICES. IT IS STRONGLY RECOMMENDED THAT THIS IMPORTANT NOTE BE COMMUNICATED TO THE OWNER AND OR OPERATOR OF THE INSTALLATION AT THE TIME OF SITE COMMISSIONING. GOOD PRACTICE DOES NOT RECOMMEND THE 24/7 USE OF PRODUCTS WITHOUT THE APPLICATION OF SUITABLE SWITCH CYCLE INTERVALS. PIERLITE AUSTRALIA IS NOT RESPONSIBLE FOR ANY PRODUCT NOT MAINTAINED IN ACCORDANCE WITH THE RECOMMENDED PROCEDURES. ALL PRODUCTS SHOULD BE THOROUGHLY CLEANED ON A REGULAR BASIS TO ENSURE THE OPTICAL PERFORMANCE, TOGETHER WITH THE ELECTRICAL, MECHANICAL AND STRUCTURAL INTEGRITY AS DESIGNED, IS MAINTAINED THROUGHOUT THE SERVICE LIFE OF THE PRODUCT.



PierLUX PLUS



1. PRODUCT SPECIFICATION:

	PierLUX 5	PierLUX 6	PierLUX 8
Type of Protection	- Class II	Class II	Class II
IP Rating	- IP20	IP20	IP20
Nominal Voltage	- 240V	240V	240V
Circuit wattage	- 15W	20W	30W
Line current	- 0.35A	0.35A	0.7A
Important – when installing electronic or HID lighting equipment, the installer must consider the in-rush start current (if any) as documented on the control gear identification label when selecting appropriate circuit controls or protective devices.			
Power factor	- 0.9	0.9	0.95
Nominal Freq. (Hz)	- 50 Hz	50Hz	50Hz
Rated Maximum Ambient Temperature	- 40°C	40°C	40°C
Suitable for direct mounting on flammable surfaces	- NO		
Dimmable (if relevant refer www.pierlite.com approved list)	- NO		
Installation orientation	- Recessed horizontal interior spaces		
Designed application	- Commercial		

2. APPROVALS: The RCM marking of this product applies to AS/NZS CISPR15:2006 (EMC) "Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment". This product is designed to conform to AS/NZS60598 "Luminaires, general requirements and tests".



3. STORAGE: Prior to installation products are to be stored in cool and dry conditions.

4. APPLICATION: The installation application and orientation of the product is designed in accordance with the nominated product IP rating, class designation and these installation installations. Installation environments outside these conditions are not recommended.

5. INSTALLATION / GENERAL: Installation of the product is to be completed by an authorized and licenced electrician, in accordance with these instructions, relevant Australia standards and local regulations (where applicable). All cable terminations must be installed in accordance with the designated IP rating of the product. The mounting facilities provided for the transformer (if any), need only be utilized if in the application of the product is required by AS/NZS3000. **For electronic control equipment (when supplied) DO NOT MEGGER between A and N.**

6. INSTALLATION / SPECIAL CONDITIONS (relevant only for products approved for such an installation):

(a) products installed in high wind environments must have suitable installation / fastening methods applied to ensure the product's mounting points are not damaged through, corrosion, constant vibration and or movement. Exterior products are

designed with precise vertical aiming limits, which should not be exceeded.

(b) Products installed in corrosive or salt laden environments require special consideration and such; specific product selection, inclusive of suitable fastening methods and extensive ongoing maintenance of products installed in these environments require professional advice. It is essential that all aspects of the product selection, material specification and maintenance are specifically designed for such use.

(c) Interior highbay products must be vertically suspended. The method of suspension (chain etc) must be able to support at least 5 times the total weight of the fitting. Do not install where air movement will cause the fitting to swing about, causing wear and tear of attachment points. Luminaires should be installed where access for maintenance is practical and allows for maintenance to be completed in accordance with the manufacturer's recommendations.

(d) Interior (downlight) products must be installed to ensure the lamp unit or the driver is not covered with any combustible materials or insulation; minimum spacing's nominated for these materials are mandatory. Abutment to the downlight trim with formed thermal insulation bats at a maximum of 95mm depth is permissible in accordance with the product's thermal rating limits stated in the "product specification" above, conditional no element of the downlight thermal management fins are covered. A minimum clearance of 100mm is required above the luminaire from all materials. For dimming purposes please see www.pierlite.com for the dimming compatibility chart. When mounting multiple fixtures to conductive structures, it is recommended that the structure is earthed

7. MAINTENANCE:

(a) The supply must be isolated before opening or accessing the luminaire. Product maintenance is IMPORTANT and is critical to the products designed performance. The product is to be maintained in accordance with the manufacturer's instructions. For the latest product maintenance guides please go to www.pierlite.com. Pierlite Australia is not responsible for any product not maintained in accordance with the recommended procedure or intervals.

(b) lamps (where provided): The product is designed with the supplied (LEDs) / LAMP/s and it is strongly recommended that any LAMP / (LEDs) changes (if any) be made in accordance with the type, colour and brand supplied. For recommended LAMP / LED maintenance or operating guides (inclusive of recommended product switch cycles and mandatory run-in procedures for HID and Fluorescent lamps when used with dimming circuits), Pierlite Australia recommends the application of the lamp manufacturer's operating guidelines, which can be found on manufacturer's website. Pierlite Australia is not responsible for the product performance of alternative lamp/s used. As a member of FluroCycle, Pierlite Australia encourages recycling of lamps and components..

(c) battery (where provided): The battery is designed with a rated average battery design life of 25,000 hrs in standby mode. The battery is supported with a standard 12 month warranty; conditional of the product being maintained and operated in accordance with the manufacturer's guidelines and tested in accordance with AS/NZS2293. For guidelines see product installation instructions or visit www.pierlite.com.

(d) for products supplied with glass visors or covers, do not operate the product with a damaged visor or cover; it is recommended the product be turned off, area surrounding the product vacated and the damaged glass replaced by a professional installer immediately.

8. WARRANTY INSTRUCTIONS: For the purpose of warranty claims (if any) the following instructions apply:

Warranty components – PierLUX PLUS, (identified as the LED and driver only). **Warranty period** - The above components are provided with a warranty of three (3) years (which ever arrives first) against manufacturing defects or failure to perform to specifications for products installed by an authorised installer in accordance with the manufacturer's installation instructions and which have not been subject to incorrect operation or maintenance, unauthorised modification or damage arising from any intervening cause. **Warranty reference** - The warranty reference date commences from the date of purchase.

Warranty point of contact – Pierlite Australia Pty Ltd, 96 Gow Street Padstow NSW 2211, phone +61 2 9794 9300, email lighting@pierlite.com.au, contact – Pierlite After Sales Support.

Warranty claim procedure – For the purpose of making a claim the customer must:

1. Contact the "point of contact" above and upon provision of proof of purchase the customer will receive a goods return advice (GRA) number.
2. At the customer's expense, collect and return the goods to the "point of contact" with the issued GRA number.
3. Upon receipt of the goods, Pierlite Australia will review the claim and if found to be accepted, Pierlite Australia will return a replacement product to the customer to install at the customer's expense. Alternatively if the claim is rejected, the customer may request the return of the goods at their expense.

Consumer Contracts - The benefits to the customer given by the Pierlite Australia warranty are in addition to other rights and remedies of the customer if the goods are the subject of a Consumer Contract under the Australian Consumer Law. In that event the following statement is required to be brought to the Consumer's attention:-

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

Limitation of Liability – if the goods are not purchased by the customer under a Consumer Contract within the Australian Consumer Law then but not otherwise;- (a) the Company is not liable in tort for any loss or damage suffered by the customer or by any third party; and (b) in no circumstances is Pierlite Australia liable to the customer or to any third party for any loss of profits, loss of anticipated savings, economic loss or interruption of business or for any indirect or consequential loss (Consequential Loss).

Terms of Sale – these Warranty provisions are in substitution for any inconsistent provisions in the Pierlite Australia Terms and Conditions of Sale in so far as they apply to the Warranty components.



PIERLITE AUSTRALIA PTY LTD
96-112 Gow Street
Padstow, NSW 2211
T: +61 2 9794 9300
E: lighting@pierlite.com.au
W: www.pierlite.com